

TABLE I

**TOTAL PARALLEL EQUIVALENT RESISTANCES/REACTANCES
OBTAINABLE FROM EMS MODULES 8311, 8321 AND 8331.**

EQUIVALENT RESISTANCE/ REACTANCE VALUES	FIRST SECTION CLOSED SWITCHES	SECOND SECTION CLOSED SWITCHES (PARALLEL WITH FIRST SECTION)	THIRD SECTION CLOSED SWITCHES (PARALLEL WITH OTHER SECTIONS)
1200Ω	1200	None	None
600Ω	600	None	None
300Ω	300	None	None
400Ω	1200 & 600	None	None
240Ω	1200 & 300	None	None
200Ω	600 & 300	None	None
171.4Ω	1200 & 600 & 300	None	None
150Ω	1200	1200 & 600 & 300	None
133.3Ω	600	1200 & 600 & 300	None
120Ω	300	600 & 300	None
109.1Ω	300	1200 & 600 & 300	None
100Ω	1200 & 300	1200 & 600 & 300	None
92.3Ω	600 & 300	1200 & 600 & 300	None
85.7Ω	1200 & 600 & 300	1200 & 600 & 300	None
80Ω	1200	1200 & 600 & 300	1200 & 600 & 300
75Ω	600	1200 & 600 & 300	1200 & 600 & 300
70.6Ω	300	600 & 300	1200 & 600 & 300
66.7Ω	300	1200 & 600 & 300	1200 & 600 & 300
63.1Ω	1200 & 300	1200 & 600 & 300	1200 & 600 & 300
60Ω	600 & 300	1200 & 600 & 300	1200 & 600 & 300
57.1Ω	1200 & 600 & 300	1200 & 600 & 300	1200 & 600 & 300

NOTE: Many parallel combinations, (other than shown) can be used to obtain the same equivalent resistance/reactance values listed.